

Rated voltage \* 208/240 volts

Québec

Canada

	Unit	MCA	MOCOP	MCA x 1.2 AWG	MCA x 1.2 Breaker	AWG	MCA x 1.25 Breaker
ECO Condenser	WLUD24W2/D-D(U)	19.5	30	23.4 (12AWG)	23.4 (30amp)	19.5 (12AWG)	24.3 (30amp)
	WLUD30W2/D-D(U)	20.5	35	24.6 (12AWG)	24.6 (30amp)	20.5 (12AWG)	25.6 (30amp)
	WLUD36W2/D-D(U)	24	40	28.8 (10AWG)	28.8 (30amp)	24 (12AWG)	30 (30amp)
Ultraheat Condenser	WLUD36W/A-D(U)	24	35	28.8 (10AWG)	28.8 (30amp)	24 (12AWG)	30 (30amp)
	WLUD60W/A-D(U)	35	45	42 (8AWG)	42 (50amp)	35 (10AWG)	43.8 (50amp)
Multizone	WLWHD(18)ND3PO	15	20	18 (12AWG)	18 (20amp)	15 (14AWG)	18.8 (20amp)
	WLWHD(24)ND3MO	19	25	22.8 (12AWG)	22.8 (30amp)	19 (12AWG)	23.8 (30amp)
	WLWHD(30)ND3MO	23	35	27.6 (10AWG)	27.6 (30amp)	23 (12AWG)	28.8 (30amp)
	WLWHD(36)ND3MO	29	45	34.8 (10AWG)	34.8 (40amp)	29 (10AWG)	36.3 (40amp)
	WLWHD(42)ND3MO	29	45	34.8 (10AWG)	34.8 (40amp)	29 (10AWG)	36.3 (40amp)

Rated voltage \* 208/240 volts

Québec

Canada

	Unit	MCA	MOCP	MCA x 1.2 AWG	MCA x 1.2 Breaker	AWG	MCA x 1.25 Breaker
Pular	WLWH09AGCXD-D3DNA1A/O	10	15	12 (14AWG)	12 (15amp)	10 (14AWG)	12.6 (15amp)
	WLWH12AGCXD-D3DNA1A/O	10	15	12 (14AWG)	12 (15amp)	10 (14AWG)	12.6 (15amp)
	WLWH18QDXF-D3DNB2A/O	15	20	18 (12AWG)	18 (20amp)	15 (14AWG)	18.8 (20amp)
	WLWH24AGEXH-D3DNA1A/O	16	25	19.2 (12AWG)	19.2 (20amp)	16 (12AWG)	20 (20amp)
Charmo	WLW09HQ19SDO	9	15	10.8 (14AWG)	10.8 (15amp)	9 (14AWG)	11.3 (15amp)
	WLW12HQ19SDO	11	15	13.2 (14AWG)	13.2 (15amp)	11 (14AWG)	13.8 (15amp)
	WLW18HQ19SDO	14	20	16.8 (12AWG)	16.8 (20amp)	14 (14AWG)	17.5 (20amp)
	WLW24HQ19SDO	15	20	18 (12AWG)	18 (20amp)	15 (14AWG)	18.8 (20amp)

Rated voltage \* 208/240 volts

Ultraheat  
Air Handler

Unit	MCA	MOCP	MCA x 1.2 AWG	MCA x 1.2 Breaker	AWG	MCA x 1.25 Breaker
WLUD36AH2/A-D(U)	4	15			5 (14AWG)	5 (15amp)
WLUD60AH2/A-D(U)	8	15			10 (14AWG)	10 (15amp)
Duct Heater 5KW	20.8				20.8 (12AWG)	26 (30amp)
Duct Heater 8KW	33.3				33.3 (10AWG)	41.6 (50amp)
Duct Heater 10KW	41.6				41.6 (8AWG)	52 (60amp)
Duct Heater 15KW	62.5				62.5 (6AWG)	78.1 (80amp)
Duct Heater 20KW	83.3				83.3 (4AWG)	104.1 (125amp)